

มหาวิทยาลัยเชียงใหม่
Chiang Mai University

ภาคผนวก

ภาคผนวก ก.

ตารางแสดงค่าสัมประสิทธิ์การคำนวณหาความเข้มรังสีอาทิตย์

ตารางที่ ก-1 ค่าความเข้มรังสีอาทิตย์และค่าสัมประสิทธิ์ของชั้นบรรยากาศ [11]

เดือน	A (Btu/hr-ft ²)	B	C
มกราคม	390	0.142	0.058
กุมภาพันธ์	385	0.144	0.060
มีนาคม	376	0.156	0.071
เมษายน	360	0.180	0.097
พฤษภาคม	350	0.196	0.121
มิถุนายน	345	0.205	0.134
กรกฎาคม	344	0.207	0.136
สิงหาคม	351	0.201	0.122
กันยายน	365	0.177	0.092
ตุลาคม	378	0.160	0.073
พฤศจิกายน	387	0.149	0.063
ธันวาคม	391	0.142	0.057

ตารางที่ ก-2 แสดงค่าสัมประสิทธิ์ของสมการอนุกรมกำลัง [4]

i	a_i	b_i
0	1.1049	0.9864
1	-1.4354	-0.2001
2	-1.0720	-1.1883
3	6.6849	3.3705
4	-13.8990	-5.7674
5	13.0798	3.7206
6	-4.4631	-0.9217

ตารางที่ ก-3 ค่าสัมประสิทธิ์ของจังหวัดเชียงใหม่ [5]

วันที่	a_0	b_0
14 ม.ค. - 26 ก.พ.	0.321	0.678
27 ก.พ. - 12 เม.ย.	0.326	0.673
13 เม.ย. - 28 พ.ค.	0.400	0.599
29 พ.ค. - 15 ก.ค.	0.395	0.604
16 ก.ค. - 31 ส.ค.	0.393	0.606
1 ก.ย. - 15 ต.ค.	0.345	0.654
16 ต.ค. - 29 พ.ย.	0.361	0.638
30 พ.ย. - 13 ม.ค.	0.366	0.633

ตารางที่ ก-4 ค่าสัมประสิทธิ์ของกรุงเทพมหานคร [5]

วันที่	a_0	b_0
14 ม.ค. - 26 ก.พ.	0.368	0.631
27 ก.พ. - 12 เม.ย.	0.324	0.675
13 เม.ย. - 28 พ.ค.	0.352	0.647
29 พ.ค. - 15 ก.ค.	0.404	0.595
16 ก.ค. - 31 ส.ค.	0.410	0.589
1 ก.ย. - 15 ต.ค.	0.363	0.636
16 ต.ค. - 29 พ.ย.	0.382	0.617
30 พ.ย. - 13 ม.ค.	0.382	0.617

ภาคผนวก ข.

โปรแกรมการวิเคราะห์ขนาดระบบไฟโตโวลตาอิก

โปรแกรมที่ 1 คำนวณหาค่าเฉลี่ยชั่วโมงความยาวนานแสงแดดตลอดปี

%Program Calculated mean sunshine hours per Day.

%Name mean_sun.m

```
load sunshine1.dat;%size(5,44)
load sunshine2.dat;%size(5,46)
load sunshine3.dat;%size(5,46)
load sunshine4.dat;%size(5,48)
load sunshine5.dat;%size(5,47)
load sunshine6.dat;%size(5,45)
load sunshine7.dat;%size(5,45)
load sunshine8.dat;%size(5,45)

format bank;
%data_day = input('Please select type of day either during 1 or 2 = ');
data_day = 1;
if data_day == 1;
sunshine1 = sunshine1 ;
sunshine2 = sunshine2 ;
sunshine3 = sunshine3 ;
sunshine4 = sunshine4 ;
sunshine5 = sunshine5 ;
sunshine6 = sunshine6 ;
sunshine7 = sunshine7 ;
sunshine8 = sunshine8 ;
else data_day == 2;
data1 = zeros(10,44); % size(10,44)
data1([1:5],[1:2:43]) = sunshine1(:,[1:2:43]); % sunshine1 Row 1-5
data1([6:10],[1:2:43]) = sunshine1(:,[2:2:44]);% sunshine1 Row 6-10
data1(:,[2:2:44]) = data1(:,[1:2:43]);% Double Column
sunshine1 = data1; % data sunshine1 size (10,44)
data2 = zeros(10,46); % size(10,46)
data2([1:5],[1:2:45]) = sunshine2(:,[1:2:45]);
data2([6:10],[1:2:45]) = sunshine2(:,[2:2:46]);
data2(:,[2:2:46]) = data2(:,[1:2:45]);
sunshine2 = data2; % data sunshine2 size (10,46)
```

```

data3 = zeros(10,46); % size(10,46)
data3([1:5],[1:2:45]) = sunshine3(:,[1:2:45]);
data3([6:10],[1:2:45]) = sunshine3(:,[2:2:46]);
data3(:,[2:2:46]) = data3(:,[1:2:45]);
sunshine3 = data3; % data sunshine3 size (10,46)
data4 = zeros(10,48); % size(10,48)
data4([1:5],[1:2:47]) = sunshine4(:,[1:2:47]);
data4([6:10],[1:2:47]) = sunshine4(:,[2:2:48]);
data4(:,[2:2:48]) = data4(:,[1:2:47]);
sunshine4 = data4; % data sunshine4 size (10,48)
data5 = zeros(10,47); % size(10,47)
data5([1:5],[1:2:45]) = sunshine5(:,[1:2:45]);
data5([6:10],[1:2:45]) = sunshine5(:,[2:2:46]);
data5(:,[2:2:46]) = data5(:,[1:2:45]);
data5([1:5],47) = sunshine5([1:5],47);
data5([6:10],47) = sunshine5([6:10],47);
sunshine5 = data5; % data sunshine5 size (10,47)
data6 = zeros(10,45); % size(10,45)
data6([1:5],[1:2:43]) = sunshine6(:,[1:2:43]);
data6([6:10],[1:2:43]) = sunshine6(:,[2:2:44]);
data6(:,[2:2:44]) = data6(:,[1:2:43]);
data6([1:5],45) = sunshine6([1:5],45);
data6([6:10],45) = sunshine6([6:10],45);
sunshine6 = data6; % data sunshine6 size (10,45)
data7 = zeros(10,45); % size(10,45)
data7([1:5],[1:2:43]) = sunshine7(:,[1:2:43]);
data7([6:10],[1:2:43]) = sunshine7(:,[2:2:44]);
data7(:,[2:2:44]) = data7(:,[1:2:43]);
data7([1:5],45) = sunshine7([1:5],45);
data7([6:10],45) = sunshine7([6:10],45);
sunshine7 = data7; % data sunshine7 size (10,45)
data8 = zeros(10,45); % size(10,45)
data8([1:5],[1:2:43]) = sunshine8(:,[1:2:43]);
data8([6:10],[1:2:43]) = sunshine8(:,[2:2:44]);
data8(:,[2:2:44]) = data8(:,[1:2:43]);
data8([1:5],45) = sunshine8([1:5],45);
data8([6:10],45) = sunshine8([6:10],45);
sunshine8 = data8; % data sunshine8 size (10,45)
end

```

```

% save mean daily of sunshine duration data (total 366 day in a year)
save mean1.dat mean1 -ASCII;%size(1,44)
save mean2.dat mean2 -ASCII;%size(1,46)
save mean3.dat mean3 -ASCII;%size(1,46)
save mean4.dat mean4 -ASCII;%size(1,48)
save mean5.dat mean5 -ASCII;%size(1,47)
save mean6.dat mean6 -ASCII;%size(1,45)
save mean7.dat mean7 -ASCII;%size(1,45)
save mean8.dat mean8 -ASCII;%size(1,45)

```

โปรแกรมที่ 2 คำนวณหาค่าสัมประสิทธิ์ตามละติจูดของสถานที่ติดตั้งระบบ

```

% Program Calculation Coefficient of Regression
% Name cal_coeff.m
global latitude;
load coeff_cm.dat;
load coeff_bk.dat;
latitude = input('latitude of station = ');
if latitude >= 18.47;
    coefficient = coeff_cm;
elseif latitude <= 13.44;
    coefficient = coeff_bk;
else (latitude < 18.47) & (latitude > 13.44);
    slope_a0 = (coeff_bk(:,1)-coeff_cm(:,1))./(5.03);
    coeff_a0 = coeff_bk(:,1)-(slope_a0.*(13.44-latitude)); % Coefficient a0
    slope_a1 = (coeff_bk(:,2)-coeff_cm(:,2))./(5.03);
    coeff_a1 = coeff_bk(:,2)-(slope_a1.*(13.44-latitude)); % Coefficient a1
    coefficient = zeros(8,2);
    coefficient(:,1) = coeff_a0(:,:);
    coefficient(:,2) = coeff_a1(:,:);
end
save coefficient.dat coefficient -ASCII; % save coefficient value is ascii file

```

โปรแกรมที่ 3 คำนวณหาค่าสัมประสิทธิ์ตามละติจูดของสถานที่ติดตั้งระบบ

```

% Program Calculate solar hour angle , zenith angle
% name zenith.m
global longitude;
global latitude;
global tilt;
longitude = input('Longitude of local = ');
latitude = input('Latitude of local = ');
tilt = input('Module tilt angle = ');
ts = zeros(365,12);
t = [390 450 510 570 630 690 750 810 870 930 990 1050];%time
w = zeros(365,12);
delta = zeros(1,365);
for i = 1:365;
    % Solar declination Angle
    delta(i) = (23.45)*sin(((360/365)*(284+(i)))*(pi/180));%size(1,365)
    B(i) = (360/364)*(i-81);
    EOT(i) = (9.87*sin(2*B(i)*(pi/180)))-(7.53*cos(B(i)*(pi/180)))-(1.5*sin(B(i)*(pi/180)));%unit (minute)
    for j = 1:12;
        % solar time = standard time+/-4*(Lstd-Llocal)+EOT ; + for west , - for east
        x1(i,j) = -(4*(105-98.98))+EOT(i);%solar time 0-24 hour
        x2(i,j) = fix(x1(i,j)+ t(j));%round off second
        x(i,j) = fix(x2(i,j)/60);%time = hour
        ts(i,j) = x(i,j)+(((x2(i,j))-x(i,j)*60)/100);%time = hour:minute
        if ts(i,j) < 12;
            w(i,j) = -((12-ts(i,j))*15);% solar hour angle +180 to -180 , 0 degree at solar noon
        elseif ts(i,j) > 12;
            w(i,j) = (ts(i,j)-12)*15;
        else ts(i,j) == 12;
            w(i,j) = 0;
        end
    end
end
end
cos_z = zeros(365,12);
z = zeros(365,12);% zenith angle
zeta = zeros(365,12);%angle between beam tilt and beam normal
nn = zeros(365,12);%variable
for i = 1:365;
    for j = 1:12;

```

```

cos_z(i,j) = (sin(latitude*(pi/180))*sin((delta(i))*(pi/180)))+...
(cos(latitude*(pi/180))*cos((delta(i))*(pi/180))*cos((w(i,j))*(pi/180)));
z(i,j) = (acos(cos_z(i,j)))*(180/pi);%size(365,12)
if z(i,j) > 90;
z(i,j) = 90;
else
z(i,j)=z(i,j);
end
% find incident angle (zeta)
nn(i,j) = cos((latitude - tilt)*(pi/180))*cos((delta(i))*(pi/180))*cos((w(i,j))*(pi/180))+...
(sin((latitude - tilt)*(pi/180))*sin((delta(i))*(pi/180)));
zeta(i,j) = (acos(nn(i,j)))*180/pi;%size(365,12)
end
end
% save data
save z.dat z -ASCII;%zenith angle size(365,12) [degree] (zenith + alfa = 90 degree)
save zeta.dat zeta -ASCII;%beam between normal to incident angle size(365,12) [degree]
save w.dat w -ASCII;%solar hour angle size(365,12) [degree]

```

โปรแกรมที่ 4 คำนวณหาองค์ประกอบความเข้มรังสีอาทิตย์ที่ตกกระทบบนพื้นราบ

```

% Program calculate solar insolation on horizontal surface from clear sky
% Name Exell_clear.m
load z.dat; % size(365,12)
load Exell.dat; % size(7,2)
Exell = Exell*1000;
Gc = zeros(365,12);
Ic = zeros(365,12);
Dc = zeros(365,12);
for i = 1:365;
F(i) = 1-(0.0335*sin(((360*(i-94))/365)*(pi/180)));
for j = 1:12;
G(:,j) = 0;
I(:,j) = 0;
for k = 1:7;
x = [0:1:6]; % z = zenith angle [degree]
G(j,k) = (Exell(k,1))*((z(i,j)/90).^(2*x(k)));
I(j,k) = (Exell(k,2))*((z(i,j)/90).^(2*x(k)));
end
Gc(i,j) = sum(G(j,:));% Total solar insolation on horizontal surface from clear sky

```

```

Ic(i,j) = sum(I(j,:)); % Direct solar insolation on horizontal surface from clear sky
Gc(i,j) = Gc(i,j)*F(i);
Ic(i,j) = Ic(i,j)*F(i);
if z(i,j) >= 90;
    Gc(i,j) = 0;
    Ic(i,j) = 0;
else
    Gc(i,j) = Gc(i,j);
    Ic(i,j) = Ic(i,j);
end
Dc(i,j) = Gc(i,j) - (Ic(i,j)*(sin((90-z(i,j))*pi/180))); %Diffuse solar insolation on horizontal surface from clear sky
% size Gc , Ic , Dc (365,12)
end
end
save Gc.dat Gc -ASCII; %Total solar insolation size(365,12) watt/sq.metre
%size(365,12)
save Ic.dat Ic -ASCII; %Direct solar insolation size(365,12) watt/sq.metre
%size(365,12)
save Dc.dat Dc -ASCII; %Diffuse solar insolation size(365,12) watt/sq.metre
%size(365,12)

```

โปรแกรมที่ 5 คำนวณหาพลังงานแสงอาทิตย์ที่ตกกระทบบนแผงเซลล์แสงอาทิตย์ในสภาพท้องฟ้ามีเมฆ

```

% Program calculate solar insolation on tilt surface from all sky
% Name klucher_allsky.m
load mean1.dat;%size(1,44)
load mean2.dat;%size(1,46)
load mean3.dat;%size(1,46)
load mean4.dat;%size(1,48)
load mean5.dat;%size(1,47)
load mean6.dat;%size(1,45)
load mean7.dat;%size(1,45)
load mean8.dat;%size(1,45)
load coefficient.dat;%size(8,2)
load Gc.dat;%size(365,12)
load Ic.dat;%size(365,12)
load Dc.dat;%size(365,12)
load z.dat;% zenith angle (365,12)

```

```

load zeta.dat;%beam between normal to incident angle(365,12)
load w.dat;% solar hour angle (365,12)
% adjust data sunshine duration
s = zeros(1,365);
s(1,[1:44]) = mean1(:,:);
s(1,[45:89]) = mean2(1,[1:45]);%FEB set is 28 day
s(1,[90:135]) = mean3(:,:);
s(1,[136:183]) = mean4(:,:);
s(1,[184:230]) = mean5(:,:);
s(1,[231:275]) = mean6(:,:);
s(1,[276:320]) = mean7(:,:);
s(1,[321:365]) = mean8(:,:);
%Sm given by calculated daily hour from sunrise to sunset(mean)
% Sm =[10.99 11.70 12.45 12.82 12.45 11.70 10.99 10.66] from Exell
Sm = zeros(1,365);
Sm(1,[1:44]) = 10.99;
Sm(1,[45:89]) = 11.70;
Sm(1,[90:135]) = 12.45;
Sm(1,[136:183])= 12.82;
Sm(1,[184:230])= 12.45;
Sm(1,[231:275])= 11.70;
Sm(1,[276:320])= 10.99;
Sm(1,[321:365])= 10.66;
Q1(1,[1:44]) = coefficient(1,1); Q2(1,[1:44]) = coefficient(1,2);
Q1(1,[45:89]) = coefficient(2,1); Q2(1,[45:89]) = coefficient(2,2);
Q1(1,[90:135]) = coefficient(3,1); Q2(1,[90:135]) = coefficient(3,2);
Q1(1,[136:183])= coefficient(4,1); Q2(1,[136:183])= coefficient(4,2);
Q1(1,[184:230])= coefficient(5,1); Q2(1,[184:230])= coefficient(5,2);
Q1(1,[231:275])= coefficient(6,1); Q2(1,[231:275])= coefficient(6,2);
Q1(1,[276:320])= coefficient(7,1); Q2(1,[276:320])= coefficient(7,2);
Q1(1,[321:365])= coefficient(8,1); Q2(1,[321:365])= coefficient(8,2);
%Calculated solar insolation on tilt surface
Gt:lt = zeros(365,12);
Gd = zeros(365,12);
ld = zeros(365,12);
Dd = zeros(365,12);
rc = zeros(365,12);
r = zeros(365,12);

```

```

for i = 1:365; %
    % clearness factor estimate from duration of sunshine data
    kd(i) = Q1(i) + Q2(i)*((s(i))/Sm(i));%365
    for j = 1:12;
        if Gc(i,j) == 0;
            rc(i,j)= 0;
        else
            rc(i,j) = Dc(i,j)/Gc(i,j);%size(365,12) Line 70
        end
        r(i,j) = 1 -(0.733*(kd(i).^2)+(0.267*(kd(i).^4))*(1 - rc(i,j)));
        Gd(i,j) = kd(i)*Gc(i,j);
        ld(i,j) = (((1 - r(i,j))*Gd(i,j))/cos(z(i,j)*(pi/180)));
        Dd(i,j) = r(i,j)*Gd(i,j);
        if Gd(i,j) == 0;
            F(j)= 0;
        else
            F(j) = 1 -((Dd(i,j)/Gd(i,j)).^2);    % Line 80
        end
        a(j) = (sin((90-z(i,j))*(pi/180))*cos(zeta(i,j)*(pi/180)));
        if a(j) == 0;
            A(j) = 0;
        else
            A(j) = (Gd(i,j)-Dd(i,j))/sin((90-z(i,j))*(pi/180))*cos(zeta(i,j)*(pi/180));
        end
        b(j) = ((1+cos(tilt*(pi/180)))/2);    %Line 90
        if b(j) == 0;
            B(j) = 0;
        else
            B(j) = Dd(i,j)*((1+cos(tilt*(pi/180)))/2);
        end
        C(j) = 1 + F(j)*(((3/4)*sin((tilt/2)*(pi/180)))-((1/4)*sin(3*(tilt/2)*(pi/180))));
        E(j) = 1 + F(j)*((1/2)+(1/2)*(cos(2*zeta(i,j)*(pi/180)))*((3/4)*(sin(z(i,j)*(pi/180)))-...
            ((1/4)*(sin(3*z(i,j)*(pi/180)))));    %Line 100
        Gtilt(i,j) = (A(j)+(B(j))*C(j)*E(j)); %solar insolation on tilt surface size(365,12)
        if Gtilt(i,j) < 0;
            Gtilt(i,j) = 0;
        else
            Gtilt(i,j)=Gtilt(i,j);
        end
    end
end

```

```

end
end
% save total insolation on tilt surface (watt/sq.metre)
save Gklucher.dat Gtilt -ASCII;%size(365,12)

```

โปรแกรมที่ 6 ประมาณค่าอุณหภูมิแวดล้อมจากข้อมูลสถิติอุณหภูมิ

```

% Program Estimated Ambient Temperature by Polynomial Regression Methods
% Name temp_regression.m
format bank;
load data_temp1991.dat; %size (366,26)
load data_temp1992.dat; %size (366,26)
load data_temp1993.dat; %size (366,26)
load data_temp1994.dat; %size (366,26)
load data_temp1996.dat; %size (366,26)
datatemp1 = data_temp1991; %size(366,26)
datatemp2 = data_temp1992;
datatemp3 = data_temp1993;
datatemp4 = data_temp1994;
datatemp5 = data_temp1996;
% Adjust data temperature to size(366,24) and Calculated Mean Temperature
hour = 1:24;
for i = 1:366;
    temp(i,:) = (datatemp1(i,[2:25])+ datatemp2(i,[2:25])+ datatemp3(i,[2:25])...
        + datatemp4(i,[2:25])+ datatemp5(i,[2:25]))/5;% size(366,24)
end
% Calculate The Coefficient of Polynomial Regression
for i = 1:366;
    % Can changeable the number of Coefficient
    coeff_day(i,:) = polyfit(hour,temp(i,:), 10); % (366,No.coefficient)
end
% Estimate Temperature in the future (Degree Celcius)
for i = 1:366;
    temperature(i,:) = polyval(coeff_day(i,:),hour);%size(366,24)
end
% save data temperature (366,24)
save temperature.dat temperature -ASCII;

```

โปรแกรมที่ 7 คำนวณหาพลังงานไฟฟ้าที่แผงเซลล์แสงอาทิตย์ผลิตได้

```

% Progame Calculation Energy from Module
% Name PV_output.m
load Gklucher.dat; % size (365,12)
load temperature.dat ; % size(366,24)
format bank;
global I_ref;
global V_ref;
% adjust data Gtitt (365,12) is (366,24)
Gt = zeros(366,24);
Gt([1:59],[7:18]) = Gklucher([1:59],[1:12]);
Gt(60,[7:18]) = Gklucher(59,[1:12]);% 28 Feb = 29 Feb
Gt([61:366],[7:18]) = Gklucher([60:365],[1:12]);
% Data Photovoltaic Module
disp ('INPUT SPECIFICATION DATA OF PV-MODULE');
S_ref = input('Reference Solar Radiation [watt/sq.m] =');
T_ref = input('Reference temperature [Celcius] =');
Rs = input('Series Resistance of Module [Ohm] =');
I_ref = input('Rated Current of Module [Amps] =');
Isc = input('Short circuit current of Module [Amps] =');
V_ref = input('Rated Voltage of Module [Volts] =');
coeff_V = input('Coefficiene Voltage of Module [Volts/Celcius] =');
coeff_I = input('Coefficiene Current of Module [Amps/Celcius] =');
% Calculate Energy from Module (Wh/day)
Tc = zeros(366,24);%set matrix cell teperature
D_T = zeros(366,24);%set matrix delta temperature
D_I = zeros(366,24);%set matrix delta module current
D_V = zeros(366,24);%set matrix delta module voltage
Vmodule = zeros(366,24);
Imodule = zeros(366,24);
Wm = zeros(366,24);%set matrix energy from PV-module
for i = 1:366;
    for j = 7:18;
        Tc(i,j) = temperature(i,j) + ((0.02)*Gt(i,j));
        D_T(i,j) = Tc(i,j) - T_ref;
        D_I(i,j) = (coeff_V*(Gt(i,j)/S_ref)*D_T(i,j))+(((Gt(i,j)/S_ref)-1)*Isc);
        D_V(i,j) = -(coeff_V)*D_T(i,j)-(Rs*D_I(i,j));
        Vmodule(i,j) = V_ref + D_V(i,j);
    end
end

```

```

lmodule(i,j) = l_ref + D_l(i,j);
Wm(i,j) = Vmodule(i,j)*lmodule(i,j);
if Wm(i,j) <= 0;
    Wm(i,j) = 0;
end
end
end
end

```

```

% Save data Energy from Module (Watt-hours) , size(366,24)
save Wm.dat Wm -ASCII;%size(366,24)

```

โปรแกรมที่ 8 จัดข้อมูลโหลดใน 1 ปี

```

% Program Recieve Data Load
% Name dataload.m
disp('INPUT DATA LOAD');
disp('If data load every week is same put data load size (7,24) ');
disp('If data load every 2 week is same put data load size (14,24)');
disp('If data load every 3 week is same put data load size (21,24)');
disp('If data load every 4 week is same put data load size (28,24)');
%%%%%%%%%%
Load data load (ASCII file)
load load_d100n0.m;
load load_d0n100.m;
load load_d20n80.m;
load load_d30n70.m;
load load_d40n60.m;
load load_d60n40.m;
load load_d50n50.m;
load load_d80n20.m;
data_load = load_d20n80;
%%%%%%%%%%
Wl = zeros(366,24); % case is'n put the load value at this hour data load = 0
[ro,c] = size(data_load);
if ro == [7] & c == [24]; % data load every week is same
    for i = 1:52;
        d1 = [1:7:358];
        d2 = [2:7:359];
        d3 = [3:7:360];
        d4 = [4:7:361];
    end
end

```

```

d5 = [5:7:362];
d6 = [6:7:363];
d7 = [7:7:364];

Wl(d1(i,:)) = data_load(1,:); % 1 data_load size(1,24)
Wl(d2(i,:)) = data_load(2,:); % 2 data_load size(1,24)
Wl(d3(i,:)) = data_load(3,:); % 3 data_load size(1,24)
Wl(d4(i,:)) = data_load(4,:); % 4 data_load size(1,24)
Wl(d5(i,:)) = data_load(5,:); % 5 data_load size(1,24)
Wl(d6(i,:)) = data_load(6,:); % 6 data_load size(1,24)
Wl(d7(i,:)) = data_load(7,:); % 7 data_load size(1,24)

Wl(365,:) = data_load(1,:);
Wl(366,:) = data_load(2,:);

end

elseif ro == [14] & c == [24] % data load every 2 week is same
for i = 1:26;
    d1 = [1:14:351]; d8 = [8:14:358];
    d2 = [2:14:352]; d9 = [9:14:359];
    d3 = [3:14:353]; d10 = [10:14:360];
    d4 = [4:14:354]; d11 = [11:14:361];
    d5 = [5:14:355]; d12 = [12:14:362];
    d6 = [6:14:356]; d13 = [13:14:363];
    d7 = [7:14:357]; d14 = [14:14:364];

    Wl(d1(i,:)) = data_load(1,:);
    Wl(d2(i,:)) = data_load(2,:);
    Wl(d3(i,:)) = data_load(3,:);
    Wl(d4(i,:)) = data_load(4,:);
    Wl(d5(i,:)) = data_load(5,:);
    Wl(d6(i,:)) = data_load(6,:);
    Wl(d7(i,:)) = data_load(7,:);
    Wl(d8(i,:)) = data_load(8,:);
    Wl(d9(i,:)) = data_load(9,:);
    Wl(d10(i,:)) = data_load(10,:);
    Wl(d11(i,:)) = data_load(11,:);
    Wl(d12(i,:)) = data_load(12,:);
    Wl(d13(i,:)) = data_load(13,:);
    Wl(d14(i,:)) = data_load(14,:);

    Wl(365,:) = data_load(1,:);
    Wl(366,:) = data_load(2,:);

end

```

```
elseif ro == [21] & c == [24]; % data load every 3 week is same
```

```
for i = 1:17;
```

```
    d1 = [1:21:337]; d8 = [8:14:344];    d15 = [15:21:351];
```

```
    d2 = [2:21:338]; d9 = [9:14:345];    d16 = [16:21:352];
```

```
    d3 = [3:21:339]; d10 = [10:14:346]; d17 = [17:21:353];
```

```
    d4 = [4:21:340]; d11 = [11:14:347]; d18 = [18:21:354];
```

```
    d5 = [5:21:341]; d12 = [12:14:348]; d19 = [19:21:355];
```

```
    d6 = [6:21:342]; d13 = [13:14:349]; d20 = [20:21:356];
```

```
    d7 = [7:21:343]; d14 = [14:14:350]; d21 = [21:21:357];
```

```
    Wl(d1(i,:),:) = data_load(1,:);
```

```
    Wl(d2(i,:),:) = data_load(2,:);
```

```
    Wl(d3(i,:),:) = data_load(3,:);
```

```
    Wl(d4(i,:),:) = data_load(4,:);
```

```
    Wl(d5(i,:),:) = data_load(5,:);
```

```
    Wl(d6(i,:),:) = data_load(6,:);
```

```
    Wl(d7(i,:),:) = data_load(7,:);
```

```
    Wl(d8(i,:),:) = data_load(8,:);
```

```
    Wl(d9(i,:),:) = data_load(9,:);
```

```
    Wl(d10(i,:),:) = data_load(10,:);
```

```
    Wl(d11(i,:),:) = data_load(11,:);
```

```
    Wl(d12(i,:),:) = data_load(12,:);
```

```
    Wl(d13(i,:),:) = data_load(13,:);
```

```
    Wl(d14(i,:),:) = data_load(14,:);
```

```
    Wl(d15(i,:),:) = data_load(15,:);
```

```
    Wl(d16(i,:),:) = data_load(16,:);
```

```
    Wl(d17(i,:),:) = data_load(17,:);
```

```
    Wl(d18(i,:),:) = data_load(18,:);
```

```
    Wl(d19(i,:),:) = data_load(19,:);
```

```
    Wl(d20(i,:),:) = data_load(20,:);
```

```
    Wl(d21(i,:),:) = data_load(21,:);
```

```
    Wl([358:366],:) = data_load([1:9],:);
```

```
end
```

```
elseif ro == [28] & c == [24]; % data load every 4 week is same
```

```
    Wl([1:28],:) = data_load(:,:);
```

```
    Wl([29:56],:) = data_load(:,:);
```

```
    Wl([57:84],:) = data_load(:,:);
```

```
    Wl([85:112],:) = data_load(:,:);
```

```
    Wl([113:140],:) = data_load(:,:);
```

```

WI([141:168],:) = data_load(:,:);
WI([169:196],:) = data_load(:,:);
WI([197:224],:) = data_load(:,:);
WI([225:252],:) = data_load(:,:);
WI([253:280],:) = data_load(:,:);
WI([281:308],:) = data_load(:,:);
WI([309:336],:) = data_load(:,:);
WI([337:364],:) = data_load(:,:);
WI([365:366],:) = data_load([1:2],:);
else r~= [7] | r~= [14] | r~= [21] | r~= [28] & c ~= [24]
    disp('form data load is worst(not size(7,24)or(14,24)or(21,24)or(28,24)');
    disp('Check form data load agian');
end
% save data load size (366,24)
save WI.dat WI -ASCII

```

โปรแกรมที่ 9 จำลองการทำงานของระบบและวิเคราะห์หาขนาดระบบที่เหมาะสม

```

% Program Calculate optimization
% optimize_size_t2.m
load temperature.dat;%size(366,24)
load WI.dat;%size(366,24)
load Wm.dat;%size(366,24)
global C10;
global charge_eff;
global Vbend;
global Vbover;
global Tb;
global Emax;
global Emin;
global Nc;
global factor;% set value in program2
disp('INPUT SPECIFICATION DATA OF BATTERY');
C10    = input('Battery capacity at 10 h [Ah] = ');
Vbend  = input('Battery end of voltage (at 1 Cell)[volts] = ');
Vbover = input('Battery over voltage(at 1 Cell)[volts] = ');
Tb     = input('Reference temperature of Battery [Celsius] = ');
Emax   = input('Maximum electrolyte density = ');
Emin   = input('Minimum electrolyte density = ');
Nc     = input('Number cell of battery = ');

```

```

charge_eff = input('Charger efficiency[0-1] = ');
LLP = input('Reliability level request[0-1] = ');
% Adjust data to 1 row
% temperature.dat size(366,24) to size(1,8784)
temp = zeros(1,8784);
for i = 1:366;
    l = [1:24:8761];
    m = [24:24:8784];
    temp(:,[l(i):m(i)]) = temperature(i,:);
end
%Adjust Wl.dat size(366,24) to size(1,8784)
WL = zeros(1,8784);
Wl_daily = zeros(1,366);
for i = 1:366
    l = [1:24:8761];
    m = [24:24:8784];
    WL(:,[l(i):m(i)]) = Wl(i,:); % Adjust = size(1,8784)
    %seperate load day and night[Wh/day or night]
    Wlday(i) = sum(WL((i),[8:16])); % day load size(1,366)
    Wlnight(i) = sum(WL((i),[1:7]))+ sum(WL((i),[17:24]));%night load size(1,366)
    Wl_daily(1,(i)) = sum(WL((i),:));% total daily load ,size(1,366)
end
% Wm.dat size(366,24) to size(1,8784)
WM = zeros(1,8784);
for i = 1:366;
    l = [1:24:8761];
    m = [24:24:8784];
    WM(:,[l(i):m(i)]) = Wm(i,:);%size(1,8784)
end
for i = 1:8784;
    if WM(1,i) <= 0; % protect case WM < 0
        WM(1,i) = 0;
    else
        WM(1,i) > 0;
        WM(1,i) = WM(1,i);
    end
end
end
% Estimate energy
global no_module;

```

```

global no_batt;
%global C10_approx;
No_module = mean(WL)/mean(WM);%estimate number of module
%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%
no_module = ceil(No_module)+ factor% IMPORTANCE IN ADJUST LLP OF SYSTEMS
%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%
WM_approx = WM .*[no_module];%size(1,8784) Energy module use simulation
Pre_module = no_module*V_ref*I_ref % monitor size PV-module before optimize
disp(['Watt']);
%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%
No_batt = (mean(Winight))/(C10*12);%estimate number of battery
%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%
no_batt = ceil(No_batt);%Number Integer(capacity[Wh]=C10*no_batt*12)
%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%
C10_approx = (C10*no_batt);%Approximate battery capacity for simulation
Pre_battery_size = C10_approx % monitor battery size before optimize
disp(['Ah']);
%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%
lbch = zeros(1,8784);%for set vector protect lbch start point value = 0
Wloss = zeros(1,8784);%loss
Wd = zeros(1,8784);%deficit
Wb = zeros(1,8784);
Vbt = zeros(1,8784);
SOC = zeros(1,8784);
Wcharge_batt = zeros(1,8784);
% START
for i = 1:8784;
    I10 = C10_approx/10; % battery current at 1 hour
    if WM_approx(i) > WL(i); % CASE(1) Energy Module over than Load
        W(i) = WM_approx(i) - WL(i);
        lbch(i) = W(i)/12; % Battery current
        Im(i) = WM_approx(i)/14; % Module Current
        Iload(i) = WL(i)/12; % Load Current
        % set initial FC
        if i == 1;
            FC(1) = 1; % initial state Cef = C10 so set FC value = 1
            Cef(1)= C10_approx;
            SOC(1)= 1;
            % Check Battery Charge voltage

```

```

E15(1) = Emax; % SOC(1)=1
Vo(1) = E15(1) + 0.856;
Vcell(1) = Vo(1)+((Ibch(1)/C10_approx)*0.451);
Vbt(1) = Vcell(1)*Nc; % Total battery terminal voltage
else
FC(i) = (1.79/(1+0.77*((Ibch(i)/I10)^0.726)))*(1+(0.0118*(temp(i)-Tb))-0.00031*((temp(i)-Tb)^2));
% Protect CASE Value = 0
if FC(i) > 1;
FC(i) = 1;
end
if FC(i) == 0;
Cef(i) = 0.001;
else
Cef(i) = Cef(i-1)*FC(i);
end
SOC(i) = SOC(i-1)+charge_eff*((Im(i)-Iload(i))/Cef(i));
if SOC(i) > 1;
SOC(i) = 1;
end
if SOC(i) == 0;
E15(i) = Emin;
else
E15(i) = (Emax-Emin)*SOC(i)+Emin;
end
% end
% Check Battery Charge voltage
Vo(i) = E15(i) + 0.856;
Vcell(i) = Vo(i) + (Ibch(i)/C10_approx)*((0.74/(1.05-SOC(i)))+0.451+(0.219*((FC(i)^5.74)-1)));
Vbt(i) = Vcell(i)*Nc; % battery terminal voltage
end
% Check Battery state of charge
if (Vcell(i) >= Vbend) & (Vcell(i) <= Vbover); % Charge battery
if i == 1;
Wloss(1) = 0;%
Wd(1) = 0;
Wb(1) = C10_approx.*12;
Wcharge_batt(i) = 0;
elseif i > 1;
Wloss(i) = 0; % Energy can storage in battery

```

```

Wd(i) = 0;
Wb(i) = Cef(i)*Vbt(i);
Wcharge_batt(i) = W(i)*charge_eff;%Energy input to battery
end
elseif Vcell(i) > Vbover; % Energy loss CASE Over charge
    FC(i) = 1;
    Cef(i) = C10_approx;
    SOC(i) = 1;
    E15(i) = Emax;
    Vo(i) = E15(i)+0.856;%E15 = Emax
    Vcell(i) = Vo(i)+0.451;% Set battery capacity is full
    Vbt(i) = Vcell(i)*Nc;
    Wloss(i) = W(i);% because Vcell > Vbover ( Overcharge)Energy loss
    Wd(i) = 0;
    Wb(i) = C10_approx*Vbt(i); % battery full
    Wcharge_batt(i) = 0;
end
elseif WM_approx(i) == WL(i); % CASE (2) Energy Module balance Load
    Wcharge_batt(i) = 0;
    Wloss(i) = 0;
    Wd(i) = 0;
    Wb(i) = WCb(i-1);
    FC(i) = FC(i-1);
    Cef(i) = Cef(i-1);
    SOC(i) = SOC(i-1);
    E15(i) = E15(i-1);
    Vo(i) = Vo(i-1);
    Vcell(i) = Vcell(i-1);
    Vbt(i) = Vbt(i-1);
else WM_approx(i) < WL(i); % CASE (3) Module + Battery supply Load
    W(i) = WL(i) - WM_approx(i);
    Ibdis(i) = W(i)/12; % Battery discharge current or load current [Amps]
    Wcharge_batt(i) = 0;
% set initial value
if i == 1;
    FC(1) = 1;
    Cef(1) = C10_approx;
    SOC(1) = 0;
    E15(1) = Emax; % because SOC(1)

```



```

Pre_reliability = up1/up2 %monitor reliability systems before optimize
% Adjust Wm and Wb
format bank;
for i = 1:366;
    l = [1:24:8761];
    m = [24:24:8784];
    a = [6:24:8766];%time 06.00-18.00
    b = [18:24:8778];%time 06.00-18.00
    c = [1:24:8761];%time 01.00-05.00
    d = [5:24:8765];%time 01.00-05.00
    e = [19:24:8779];%time 19.00-24.00
    f = [24:24:8784];%time 19.00-24.00

    Wm_daily(i) = sum(WM_approx(:,l(i):m(i)))/%size(1,366)** total daily energy produce
    Wb_daily(i) = (sum(Wb(:,l(i):m(i))))/24;%size(1,366)** daily energy storage in battery
    Wbday(i) = sum(Wb(:,a(i):b(i))); %battery energy noon size(1,366)
    Wbnight(i) = sum(Wb(:,c(i):d(i)))+ sum(Wb(:,e(i):f(i)))/%battery energy night size(1,366)
end
% Energy of PV-Module
EPV1 = sum(WM_approx(1,[313:1368]));%size(1,1056)
EPV2 = sum(WM_approx(1,[1369:2472]));%size(1,1104)
EPV3 = sum(WM_approx(1,[2473:3576]));%size(1,1104)
EPV4 = sum(WM_approx(1,[3577:4728]));%size(1,1152)
EPV5 = sum(WM_approx(1,[4729:5856]));%size(1,1128)
EPV6 = sum(WM_approx(1,[5857:6936]));%size(1,1080)
EPV7 = sum(WM_approx(1,[6937:8016]));%size(1,1080)
EPV([1:312]) = WM_approx(1,[1:312]);%size(1,1080)
EPV([313:1080]) = WM_approx(1,[8017:8784]);
EPV8 = sum(EPV);
% Demand Load
EL1 = sum(WL(1,[313:1368]));%size(1,1056)
EL2 = sum(WL(1,[1369:2472]));%size(1,1104)
EL3 = sum(WL(1,[2473:3576]));%size(1,1104)
EL4 = sum(WL(1,[3577:4728]));%size(1,1152)
EL5 = sum(WL(1,[4729:5856]));%size(1,1128)
EL6 = sum(WL(1,[5857:6936]));%size(1,1080)
EL7 = sum(WL(1,[6937:8016]));%size(1,1080)
EL([1:312]) = WL(1,[1:312]);%size(1,1080)

```

```

EL([313:1080]) = WL(1,[8017:8784]);
EL8 = sum(EL);
EB1 = sum(Wcharge_batt([313:1368]));
EB2 = sum(Wcharge_batt([1369:2472]));
EB3 = sum(Wcharge_batt([2473:3576]));
EB4 = sum(Wcharge_batt([3577:4728]));
EB5 = sum(Wcharge_batt([4729:5856]));
EB6 = sum(Wcharge_batt([5857:6936]));
EB7 = sum(Wcharge_batt([6937:8016]));
EB([1:312]) = Wcharge_batt([1:312]);
EB([313:1080]) = Wcharge_batt([8017:8784]);
EB8 = sum(EB);
% Energy loss
Eloss1 = sum(Wloss([14:57]));
Eloss2 = sum(Wloss([58:103]));
Eloss3 = sum(Wloss([104:149]));
Eloss4 = sum(Wloss([150:197]));
Eloss5 = sum(Wloss([198:244]));
Eloss6 = sum(Wloss([245:289]));
Eloss7 = sum(Wloss([290:334]));
Eloss([1:32]) = Wloss([335:366]);
Eloss([33:45]) = Wloss([1:13]);
Eloss8 = sum(Eloss);
%#####
global Zmin;
Aeq = [(EPV1-EB1) (EB1);
        (EPV2-EB2) (EB2);
        (EPV3-EB3) (EB3);
        (EPV4-EB4) (EB4);
        (EPV5-EB5) (EB5);
        (EPV6-EB6) (EB6);
        (EPV7-EB7) (EB7);
        (EPV8-EB8) (EB8)];
beq = [EL1*(1-LLP);
        EL2*(1-LLP);
        EL3*(1-LLP);
        EL4*(1-LLP);
        EL5*(1-LLP);
        EL6*(1-LLP);

```

```

EL7*(1-LLP);
EL8*(1-LLP)];
LB = [1 ; 0.1];
UP = [100;100];
f = [(no_module*V_ref*I_ref); ((C10_approx)*12)];
Zmin = linprog(f,[],[],Aeq,beq,LB,UP)

```

โปรแกรมที่ 10 ตรวจสอบความน่าเชื่อถือในการจ่ายกำลังไฟฟ้าของระบบ

```

% Program check answer
% test_klucher2.m
load temperature.dat;
load Wl.dat;
load Wm.dat;
% Adjust data to 1 row 8784 column
% temperature.dat size(366,24) to size(1,8784)
temp = zeros(1,8784);
for i = 1:366;
    l = [1:24:8761];
    m = [24:24:8784];
    temp(:,[l(i):m(i)]) = temperature(i,:);
end
% Adjust Wl.dat size(366,24) to size(1,8784)
WL = zeros(1,8784);
%WL_daily = zeros(1,366);
for i = 1:366
    l = [1:24:8761];
    m = [24:24:8784];
    WL(:,[l(i):m(i)]) = Wl(i,:); % Adjust = size(1,8784)
end
% Wm.dat size(366,24) to size(1,8784)
WM = zeros(1,8784);
for i = 1:366;
    l = [1:24:8761];
    m = [24:24:8784];
    WM(:,[l(i):m(i)]) = Wm(i,:);%size(1,8784)
end
for i = 1:8784;
    if WM(1,i) <= 0; % protect case WM < 0
        WM(1,i) = 0;
    end
end

```

```

else
    WM(1,i) > 0;
    WM(1,i) = WM(1,i);
end
end
% Actual Energy module after Optimize
WM_approx = zeros(1,8784);
%+++++
WM_approx = WM .* (no_module*Zmin(1));
%+++++
% Actual Battery capacity after Optimize
%-----
%amp_hour = input('battery capacity = ');
C1 = C10_approx*Zmin(2);
%-----
lbch = zeros(1,8784);
lload = zeros(1,8784);
lbdis = zeros(1,8784);
lm = zeros(1,8784);
Wloss = zeros(1,8784);
Wd = zeros(1,8784);
Wb = zeros(1,8784);
Vbt = zeros(1,8784);
Vcell = zeros(1,8784);
Vo = zeros(1,8784);
SOC = zeros(1,8784);
E15 = zeros(1,8784);
FC = zeros(1,8784);
Cef = zeros(1,8784);
% START
for i = 1:8784;
    I10 = C1/10; % battery current at 1 hour
    if WM_approx(i) > WL(i); % CASE(1) Energy Module over than Load
        W(i) = WM_approx(i) - WL(i);
        lbch(i) = W(i)/12; % Battery current
        lm(i) = WM_approx(i)/14; % Module Current
        lload(i) = WL(i)/12; % Load Current

    % set initial FC

```

```

if i == 1;
    FC(1) = 1; % initial state Cef = C10 so set FC value = 1
    Cef(1) = C1;
    SOC(1) = 1;
    % Check Battery Charge voltage
        E15(1) = Emax; % SOC(1)=1
        Vo(1) = E15(1) + 0.856;
        Vcell(1) = Vo(1) + ((lbch(1)/C10_approx)*0.451);
        Vbt(1) = Vcell(1)*Nc; % Total battery terminal voltage
    else
        FC(i) = (1.79/(1+0.77*((lbch(i)/110)^0.726)))*(1+(0.0118*(temp(i)-Tb))-0.00031*((temp(i)-Tb)^2));
    % Protect CASE Value = 0
        if FC(i) > 1;
            FC(i) = 1;
        end
        if FC(i) == 0;
            Cef(i) = 0.001;
        else
            Cef(i) = Cef(i-1)*FC(i);
        end
        SOC(i) = SOC(i-1)+charge_eff*((Im(i)-Iload(i))/Cef(i));
        if SOC(i) > 1;
            SOC(i) = 1;
        end
        if SOC(i) == 0;
            E15(i) = Emin;
        else
            E15(i) = (Emax-Emin)*SOC(i)+Emin;
        end
    % end
        % Check Battery Charge voltage
            Vo(i) = E15(i) + 0.856;
            Vcell(i) = Vo(i) + (lbch(i)/C10_approx)*((0.74/(1.05-SOC(i)))+0.451+(0.219*((FC(i)^5.74)-1)));
            Vbt(i) = Vcell(i)*Nc; % battery terminal voltage
        end
        % Check Battery state of charge
        if (Vcell(i) >= Vbend) & (Vcell(i) <= Vbover); % Charge battery
            if i == 1;
                Wloss(1) = 0;%

```

```

Wd(1) = 0;
Wb(1) = C1.*12;
elseif i > 1;
    Wloss(i) = 0; % Energy can storage in battery
    Wd(i) = 0;
    Wb(i) = Cef(i)*Vbt(i);
end
elseif Vcell(i) > Vbover, % Energy loss CASE Over charge
    FC(i) = 1;
    Cef(i) = C1;
    SOC(i) = 1;
    E15(i) = Emax;
    Vo(i) = E15(i)+0.856;%E15 = Emax
    Vcell(i) = Vo(i)+0.451;% Set battery capacity is full
    Vbt(i) = Vcell(i)*Nc;
    Wloss(i) = W(i);% because Vcell > Vbover ( Overcharge)Energy loss
    Wd(i) = 0;
    Wb(i) = C1*Vbt(i); % battery full
end
elseif WM_approx(i) == WL(i); % CASE (2) Energy Module balance Load

    Wloss(i) = 0;
    Wd(i) = 0;
    Wb(i) = WCb(i-1);
    FC(i) = FC(i-1);
    Cef(i) = Cef(i-1);
    SOC(i) = SOC(i-1);
    E15(i) = E15(i-1);
    Vo(i) = Vo(i-1);
    Vcell(i) = Vcell(i-1);
    Vbt(i) = Vbt(i-1);
else WM_approx(i) < WL(i); % CASE (3) Module + Battery supply Load
    W(i) = WL(i) - WM_approx(i);
    ibdis(i) = W(i)/12; % Battery discharge current or load current [Amps]
    % set initial value
    if i == 1;
        FC(1) = 1;
        Cef(1)= C1;
        SOC(1)= 0;

```



```
% ENERGY DEFICIT
```

```
d1 = Wd(:,[313:1368]);% size(1,1056)
d2 = Wd(:,[1369:2472]);% size(1,1104)
d3 = Wd(:,[2473:3576]);% size(1,1104)
d4 = Wd(:,[3577:4728]);% size(1,1152)
d5 = Wd(:,[4729:5856]);% size(1,1128)
d6 = Wd(:,[5857:6936]);% size(1,1080)
d7 = Wd(:,[6937:8016]);% size(1,1080)
d8 = Wd(:,[1:312]);
d8(:,[313:1080])=Wd(:,[8017:8784]);% size(1,1080)
W1 = WL(:,[313:1368]);% size(1,1056)
W2 = WL(:,[1369:2472]);% size(1,1104)
W3 = WL(:,[2473:3576]);% size(1,1104)
W4 = WL(:,[3577:4728]);% size(1,1152)
W5 = WL(:,[4729:5856]);% size(1,1128)
W6 = WL(:,[5857:6936]);% size(1,1080)
W7 = WL(:,[6937:8016]);% size(1,1080)
W8 = WL(:,[1:312]);
W8(:,[313:1080])=WL(:,[8017:8784]);% size(1,1080)
```

```
% MONITOR
```

```
Number_module = no_module*Zmin(1); %no_module may be fraction ut to factor value
%disp ('Panel')
Module_power = (Number_module *V_ref *I_ref)
disp('Watt')%;
Battery_capacity = [C1]
disp('Ah');
disp('Reliability system in each duration');
Reliability_1 = (sum(d1))/(sum(W1))
Reliability_2 = (sum(d2))/(sum(W2))
Reliability_3 = (sum(d3))/(sum(W3))
Reliability_4 = (sum(d4))/(sum(W4))
Reliability_5 = (sum(d5))/(sum(W5))
Reliability_6 = (sum(d6))/(sum(W6))
Reliability_7 = (sum(d7))/(sum(W7))
Reliability_8 = (sum(d8))/(sum(W8))
disp('Total Reliability system ');
Reliability_system = (sum(Wd))/(sum(WL))
```

ภาคผนวก ค.

โปรแกรมควบคุมเครื่องวัดและโหลด

โปรแกรมควบคุมเครื่องวัด

VERSION 5.00

Begin VB.Form Form1

Caption = "Form1"

ClientHeight = 3195

ClientLeft = 60

ClientTop = 345

ClientWidth = 4680

LinkTopic = "Form1"

ScaleHeight = 3195

ScaleWidth = 4680

StartPosition = 3 'Windows Default

Begin VB.CommandButton Command2

Caption = "END"

Height = 735

Left = 1200

TabIndex = 1

Top = 2040

Width = 2415

End

Begin VB.CommandButton Command1

Caption = "RUN Measurement"

Height = 855

Left = 1200

TabIndex = 0

Top = 840

Width = 2415

End

End

Attribute VB_Name = "Form1"

Attribute VB_GlobalNameSpace = False

Attribute VB_Creatable = False

```

Attribute VB_PredeclaredId = True
Attribute VB_Exposed = False
Private Sub Command1_Click()
'%%%%%%%%% DECLARE VARIABLE %%%%%%%%%%
'Data A/D #1 (Volt , Amp)
Dim DATA_A As Single 'A/D Digit 1
Dim DATA_B As Single 'A/D Digit 2
Dim DATA_C As Single 'A/D Digit 3
'Data A/D #2 (Ambient temperature)
Dim DATA_T1 As Single 'A/D Digit 1
Dim DATA_T2 As Single 'A/D Digit 2
Dim DATA_T3 As Single 'A/D Digit 3
Dim VA As Integer 'Defined filename of Volt-Amp
Dim temp As Integer 'Defined filename of Ambient temperature
Dim w4 As Single
Dim i As Long
'%%%%%%%%%
'%%%%%%%%% SET DEFAULT VALUE %%%%%%%%%%
'date_start = Day(Date)
'date_end = 30
t = 2 ' start time
hh = 1
'%%%%%%%%%
'%%%%%%%%% START PROGRAM %%%%%%%%%%
'Do While date_start <= date_end
    loop_hour = 0
    Do While loop_hour <= 23 '*** START LOOP 24 HOURS ***
        If (t >= hh And t <= (hh + 0.02)) Then
' Set In-Out port
Out &H303, &H9B 'in port (Volt - Amp)
Out &H307, &H9B 'in port (Ambient temperature)
Out &H30B, &H80 'out port
        Print " Start loop hour "
        m = 0
        Do While m <= 7 ' In one hour measure 8 times for one point
            '%%%%%%%%% Start measurment #1 %%%%%%%%%%
            Out &H308, &H7 'Set black wire Enable
            'Wait 5 Sec
            w5sec = 1

```

```

Do While w5sec < 3000000
w5sec = w5sec + 1
Loop
'Data input #1
DATA_A = Inp(&H300)
DATA_B = Inp(&H301)
DATA_C = Inp(&H302)
'Save data VA
VA = FreeFile
Open "C:\data\VA.TXT" For Append As #VA
Print #VA, " START " ' Start VA.TXT
Print #VA, DATA_A
Print #VA, DATA_B
Print #VA, DATA_C
Close #VA
' %%%%%%%%%% END #1 %%%%%%%%%%
'%%%%%%%%% Start measurment #2 %%%%%%%%%%
Out &H308, &H6 'Set brown wire Enable
'Wait 5 Sec
w5sec = 1
Do While w5sec < 3000000
w5sec = w5sec + 1
Loop
'Data input #2
DATA_A = Inp(&H300)
DATA_B = Inp(&H301)
DATA_C = Inp(&H302)
'Save data VA
VA = FreeFile
Open "C:\data\VA.TXT" For Append As #VA
Print #VA, DATA_A
Print #VA, DATA_B
Print #VA, DATA_C
Close #VA
' %%%%%%%%%% END #2 %%%%%%%%%%
'%%%%%%%%% Start measurment #3 %%%%%%%%%%
Out &H308, &H5 'Set red wire Enable
'Wait 5 Sec
w5sec = 1

```

```

Do While w5sec < 3000000
w5sec = w5sec + 1
Loop
' Data input #3
DATA_A = Inp(&H300)
DATA_B = Inp(&H301)
DATA_C = Inp(&H302)
' Save data VA
VA = FreeFile
Open "C:\data\VA.TXT" For Append As #VA
Print #VA, DATA_A
Print #VA, DATA_B
Print #VA, DATA_C
Close #VA
' %%%%%%%%%% END #3 %%%%%%%%%%
%%%%%%%%% Start measurement #4 %%%%%%%%%%
Out &H308, &H4 'Set orange wire Enable
'Wait 5 Sec
w5sec = 1
Do While w5sec < 3000000
w5sec = w5sec + 1
Loop
' Data input #4
DATA_A = Inp(&H300)
DATA_B = Inp(&H301)
DATA_C = Inp(&H302)
' Save data VA
VA = FreeFile
Open "C:\data\VA.TXT" For Append As #VA
Print #VA, DATA_A
Print #VA, DATA_B
Print #VA, DATA_C
Close #VA
' %%%%%%%%%% END #4 %%%%%%%%%%
%%%%%%%%% Start measurement #5 %%%%%%%%%%
Out &H308, &H3 'Set yellow wire Enable
'Wait 5 Sec
w5sec = 1
Do While w5sec < 3000000

```

```

w5sec = w5sec + 1
Loop
' Data input #5
DATA_A = Inp(&H300)
DATA_B = Inp(&H301)
DATA_C = Inp(&H302)
' Save data VA
VA = FreeFile
Open "C:\data\VA.TXT" For Append As #VA
Print #VA, DATA_A
Print #VA, DATA_B
Print #VA, DATA_C
Close #VA
' %%%%%%%%%% END #5 %%%%%%%%%%
'%%%%%%%%% Start measurment #6 %%%%%%%%%%
Out &H308, &H2 'Set green wire Enable
'Wait 5 Sec
w5sec = 1
Do While w5sec < 3000000
w5sec = w5sec + 1
Loop
' Data input #6
DATA_A = Inp(&H300)
DATA_B = Inp(&H301)
DATA_C = Inp(&H302)
' Save data VA
VA = FreeFile
Open "C:\data\VA.TXT" For Append As #VA
Print #VA, DATA_A
Print #VA, DATA_B
Print #VA, DATA_C
Close #VA
' %%%%%%%%%% END #6 %%%%%%%%%%
'%%%%%%%%% Start measurment #7 %%%%%%%%%%
Out &H308, &H1 'Set blue wire Enable
'Wait 5 Sec
w5sec = 1
Do While w5sec < 3000000
w5sec = w5sec + 1

```

```

Loop
' Data input #7
DATA_A = Inp(&H300)
DATA_B = Inp(&H301)
DATA_C = Inp(&H302)
' Save data VA
VA = FreeFile
Open "C:\data\VA.TXT" For Append As #VA
Print #VA, DATA_A
Print #VA, DATA_B
Print #VA, DATA_C
Close #VA
' %%%%%%%%%%% END #7 %%%%%%%%%%%
' %%%%%%%%%%% Start measurment #8 %%%%%%%%%%%
Out &H308, &H0 'Set white wire Enable
'Wait 5 Sec.
w5sec = 1
Do While w5sec < 3000000
w5sec = w5sec + 1
Loop
' Data input #8
DATA_A = Inp(&H300)
DATA_B = Inp(&H301)
DATA_C = Inp(&H302)
' Save data VA
VA = FreeFile
Open "C:\data\VA.TXT" For Append As #VA
Print #VA, DATA_A
Print #VA, DATA_B
Print #VA, DATA_C
Print #VA, " END " ' finish VA.TXT
Close #VA
' %%%%%%%%%%% END #8 %%%%%%%%%%%
'@@@@@@@@@@@@ Read Ambient temperature @@@@@@@@@@
' Data input #8
DATA_T1 = Inp(&H304)
DATA_T2 = Inp(&H305)
DATA_T3 = Inp(&H306)
' Save data VA

```


โปรแกรมควบคุมหลอดจำลองระบบโทรศัพท์เคลื่อนที่สาธารณะ 470 เมกะเฮิรตซ์

```

Function form_0() As String
Dim con0 As Long
Out &H283, &H80 ' set card is output
Out &H287, &H80 ' set card is output
Out &H28B, &H80 ' set card is output
'0 time
.....

    Out &H288, &HFF ' disconnect
'%%%%%%%%%% Wait 1 hour %%%%%%%%%%%
con0 = 0
Do While con0 <= 580 ' 6 sec x 580 loop = 58 Min
    For x = 1 To 5000000
        A = 1
    Next x
    con0 = con0 + 1
Loop
' So that this routine is time leftover 0.5 Min
'      3 x 19 = ~ 58 Min
.....

End Function
Function form_1() As String
Dim form_1 As Long
Dim i1 As Long
Dim con1 As Long
Dim x As Long
Out &H283, &H80 ' set card is output
Out &H287, &H80 ' set card is output
Out &H28B, &H80 ' set card is output
'1 time
.....

    Out &H288, &HFF ' disconnect
'%%%%%%%%% set delay time after disconnect 27 Min
i1 = 0
Do While i1 <= 269 ' 6 Sec x 270 loop = 1620 Sec(27 Min)
    For x = 1 To 5000000
        A = 1
    Next x

```

```

i1 = i1 + 1
Loop
'%%%%%%%%%%
Out &H288, &H0 'connect
$$$$$$$$ Connect 3 Minute $$$$$$$$$$
con1 = 0
Do While con1 <= 35 * 12 * 3 = 36
  For x = 1 To 5000000
    A = 1
  Next x
con1 = con1 + 1
Loop
$$$$$$$$ End connect 3 minute $$$$$$$$$$
Out &H288, &HFF ' disconnect
'%%% set delay time after disconnect 27 Min
i1 = 0
Do While i1 <= 269 * 6 Sec x 270 loop = 1620 Sec(27 Min)
  For x = 1 To 5000000
    A = 1
  Next x
i1 = i1 + 1
Loop
'%%%%%%%%%%
' So that this routine is time leftover 3 Min
' (27 + 3 + 27 = 57 Min)
.....

End Function
Function form_2() As String
Dim form_2 As Long
Dim i2 As Long
Dim con2 As Long
Dim x As Long
Out &H283, &H80 ' set card is output
Out &H287, &H80 ' set card is output
Out &H28B, &H80 ' set card is output
'2 time
.....

Out &H288, &HFF ' disconnect
form_2 = 0

```

```

Do While form_2 <= 1 '2 loop
'%%%%%%%% set delay time before connect 30 Sec

i2 = 0

Do While i2 <= 4 ' 6 sec x 5 loop = 30 Sec
  For x = 1 To 5000000
    A = 1
  Next x
  i2 = i2 + 1
Loop
'%%%%%%%%%%
Out &H288, &H0 'connect
'$$$$$$$$ Connect 3 Minute $$$$$$$$$$
con2 = 0
Do While con2 <= 30 ' 6 sec x 31 loop = 3 Min ***
  For x = 1 To 5000000
    A = 1
  Next x
  con2 = con2 + 1
Loop
'$$$$$$$$ End connect 3 minute $$$$$$$$$$
  Out &H288, &HFF 'disconnect
  form_2 = form_2 + 1
Loop 'loop form_2
'%%%%%%%% set delay time after disconnect 51 Min
i2 = 0
Do While i2 <= 509 ' 6 Sec x 510 loop = 3060 Sec(51 Min)
  For x = 1 To 5000000
    A = 1
  Next x
  i2 = i2 + 1
Loop
'%%%%%%%%%%
' So that this routine is time leftover 2 Min
'          (0.5 x 2)+(3 x 2)+ 51 = 58 Min
'.....

End Function
Function form_3() As String
Dim form_3 As Long
Dim i3 As Long

```

```

Dim con3 As Long
Dim x As Long
Out &H283, &H80 ' set card is outport
Out &H287, &H80 ' set card is outport
Out &H28B, &H80 ' set card is outport
'3 time
*****
    Out &H288, &HFF ' disconnect
form_3 = 0
Do While form_3 <= 2 ' 3 loop
'%%%%%%%% set delay time before connect 30 Sec
    i3 = 0
    Do While i3 <= 4 ' 6 sec x 5 loop = 30 Sec
        For x = 1 To 5000000
            A = 1
        Next x
        i3 = i3 + 1
    Loop
'%%%%%%%%%%
    Out &H288, &H0 'connect
'$$$$$$$$ Connect 3 Minute $$$$$$$$$$
    con3 = 0
    Do While con3 <= 30 ' 6 sec x 31 loop = 3 Min ***
        For x = 1 To 5000000
            A = 1
        Next x
        con3 = con3 + 1
    Loop
'$$$$$$$$ End connect 3 minute $$$$$$$$$$
    Out &H288, &HFF 'disconnect
    form_3 = form_3 + 1
Loop 'loop form_3
'%%%%%%%% set delay time after disconnect 47 Min
i3 = 0
Do While i3 <= 469 ' 6 Sec x 470 loop = 2820 Sec(47 Min)
    For x = 1 To 5000000
        A = 1
    Next x
    i3 = i3 + 1

```

```

Loop
'%%%%%%%%%%
' So that this routine is time leftover 2.5 Min
'          (0.5 x 3)+(3 x 3)+ 47 = 57.5 Min
'*****

End Function
Function form_4() As String
Dim form_4 As Long
Dim i4 As Long
Dim con4 As Long
Dim x As Long
Out &H283, &H80 ' set card is outport
Out &H287, &H80 ' set card is outport
Out &H28B, &H80 ' set card is outport
'4 time
'*****

    Out &H288, &HFF ' disconnect
form_4 = 0
Do While form_4 <= 3 ' 4 loop
'%%%%%%%% set delay time before connect 30 Sec
    i4 = 0
    Do While i4 <= 4 ' 6 sec x 5 loop = 30 Sec
        For x = 1 To 5000000
            A = 1
        Next x
        i4 = i4 + 1
    Loop
'%%%%%%%%
    Out &H288, &H0 'connect
'$$$$$$$$ Connect 3 Minute $$$$$$$$$$
    con4 = 0
    Do While con4 <= 30 ' 6 sec x 31 loop = 3 Min ***
        For x = 1 To 5000000
            A = 1
        Next x
        con4 = con4 + 1
    Loop
'$$$$$$$$ End connect 3 minute $$$$$$$$$$
    Out &H288, &HFF 'disconnect

```

```

form_4 = form_4 + 1
Loop 'loop form_4
    '%% set delay time after disconnect 44 Min
    i4 = 0
    Do While i4 <= 439 ' 6 Sec x 440 loop = 2640 Sec( 44 Min)
        For x = 1 To 5000000
            A = 1
        Next x
        i4 = i4 + 1
    Loop
    '%%
' So that this routine is time leftover 2 Min
'      (0.5 x 4)+(3 x 4)+ 44 = 58 Min
*****

End Function
Function form_5() As String
Dim form_5 As Long
Dim i5 As Long
Dim con5 As Long
Dim x As Long
Out &H283, &H80 ' set card is output
Out &H287, &H80 ' set card is output
Out &H28B, &H80 ' set card is output
'5 time
*****

    Out &H288, &HFF ' disconnect
form_5 = 0
Do While form_5 <= 4 ' 5 loop
'%% set delay time before connect 30 Sec
    i5 = 0
    Do While i5 <= 4 ' 6 sec x 5 loop = 30 Sec
        For x = 1 To 5000000
            A = 1
        Next x
        i5 = i5 + 1
    Loop
    '%%
    Out &H288, &H0 'connect
'$$$$$$$$$$$$ Connect 3 Minute $$$$$$$$$$$$

```

```

con5 = 0
Do While con5 <= 30 ' 6 sec x 31 loop = 3 Min ***
  For x = 1 To 5000000
    A = 1
  Next x
  con5 = con5 + 1
  Loop
  '$$$$$$$$$ End connect 3 minute $$$$$$$$$$
  Out &H288, &HFF 'disconnect
  form_5 = form_5 + 1
Loop 'loop form_5
  '%%%%' set delay time after disconnect 40.5 Min
  i5 = 0
  Do While i5 <= 405 ' 6 Sec x 405 loop = 2430 Sec( 40.5 Min)
    For x = 1 To 5000000
      A = 1
    Next x
    i5 = i5 + 1
    Loop
    '%%%%%%%%%%'
  ' So that this routine is time leftover 2 Min
  '      (0.5 x 5)+(3 x 5)+ 40.5 = 58 Min
  '.....
End Function
Function form_6() As String
Dim form_6 As Long
Dim i6 As Long
Dim con6 As Long
Dim x As Long
Out &H283, &H80 ' set card is outport
Out &H287, &H80 ' set card is outport
Out &H28B, &H80 ' set card is outport
'6 time
'.....

  Out &H288, &HFF ' disconnect
form_6 = 0
Do While form_6 <= 5 ' 6 loop
  '%%%%' set delay time before connect 30 Sec
  i6 = 0

```

```

Do While i6 <= 4 ' 6 sec x 5 loop = 30 Sec
  For x = 1 To 5000000
    A = 1
  Next x
  i6 = i6 + 1
Loop
'%%%%%%%%%%
Out &H288, &H0 'connect
'$$$$$$$$$$$ Connect 3 Minute SSSSSSSSSSS$
con6 = 0
Do While con6 <= 30 ' 6 sec x 31 loop = 3 Min ***
  For x = 1 To 5000000
    A = 1
  Next x
  con6 = con6 + 1
Loop
'$$$$$$$$$$$ End connect 3 minute SSSSSSSSS$
  Out &H288, &HFF 'disconnect
  form_6 = form_6 + 1
Loop 'loop form_6
'%%%%%%%% set delay time after disconnect 37 Min
i6 = 0
Do While i6 <= 369 ' 6 Sec x 370 loop = 2220 Sec( 37 Min)
  For x = 1 To 5000000
    A = 1
  Next x
  i6 = i6 + 1
Loop
'%%%%%%%%%%
' So that this routine is time leftover 2 Min
'          (0.5 x 6)+(3 x 6)+ 37 = 58 Min
'.....

End Function
Function form_7() As String
Dim form_7 As Long
Dim i7 As Long
Dim con7 As Long
Dim x As Long

```

```

Out &H283, &H80 ' set card is output
Out &H287, &H80 ' set card is output
Out &H28B, &H80 ' set card is output
'7 time
*****
    Out &H288, &HFF ' disconnect
form_7 = 0
Do While form_7 <= 6 ' 7 loop
'%%%%%%%% set delay time before connect 30 Sec
    i7 = 0
    Do While i7 <= 4 ' 6 sec x 5 loop = 30 Sec
        For x = 1 To 5000000
            A = 1
        Next x
        i7 = i7 + 1
    Loop
'%%%%%%%%%%
    Out &H288, &H0 'connect
'SSSSSSSSSSSS Connect 3 Minute $$$$$$$$$$$$
    con7 = 0
    Do While con7 <= 30 ' 6 sec x 31 loop = 3 Min ***
        For x = 1 To 5000000
            A = 1
        Next x
        con7 = con7 + 1
    Loop
'SSSSSSSSSSSS End connect 3 minute $$$$$$$$$$$$
    Out &H288, &HFF 'disconnect
    form_7 = form_7 + 1
Loop 'loop form_7
'%%%%%%%% set delay time after disconnect 33.5 Min
i7 = 0
Do While i7 <= 334 ' 6 Sec x 335 loop = 2010 Sec( 33.5 Min)
    For x = 1 To 5000000
        A = 1
    Next x
    i7 = i7 + 1
Loop
'%%%%%%%%%%

```

```

' So that this routine is time leftover 2 Min
'          (0.5 x 7)+(3 x 7)+ 33.5 = 58 Min
*****

End Function
Function form_8() As String
Dim form_8 As Long
Dim i8 As Long
Dim con8 As Long
Dim x As Long
Out &H283, &H80 ' set card is output
Out &H287, &H80 ' set card is output
Out &H28B, &H80 ' set card is output
'8 time
*****

    Out &H288, &HFF ' disconnect
form_8 = 0
Do While form_8 <= 7 ' 8 loop
'%%%%%%%% set delay time before connect 30 Sec
    i8 = 0
    Do While i8 <= 4 ' 6 sec x 5 loop = 30 Sec
        For x = 1 To 5000000
            A = 1
        Next x
        i8 = i8 + 1
    Loop
    '%%%%%%%%%%
    Out &H288, &H0 'connect
    '$$$$$$$$$$ Connect 3 Minute $$$$$$$$$$
    con8 = 0
    Do While con8 <= 30 ' 6 sec x 31 loop = 3 Min ***
        For x = 1 To 5000000
            A = 1
        Next x
        con8 = con8 + 1
    Loop
    '$$$$$$$$$$ End connect 3 minute $$$$$$$$$$
    Out &H288, &HFF 'disconnect
    form_8 = form_8 + 1
Loop 'loop form_8

```

```

'%%%%%%%% set delay time after disconnect 30 Min
i8 = 0
Do While i8 <= 299 ' 6 Sec x 300 loop = 1800 Sec( 30 Min)
  For x = 1 To 5000000
    A = 1
  Next x
  i8 = i8 + 1
Loop
'%%%%%%%%%%
' So that this routine is time leftover 2 Min
'      (0.5 x 8)+(3 x 8)+ 30 = 58 Min
.....

End Function
Function form_9() As String
Dim form_9 As Long
Dim i9 As Long
Dim con9 As Long
Dim x As Long
Out &H283, &H80 ' set card is outport
Out &H287, &H80 ' set card is outport
Out &H28B, &H80 ' set card is outport
'9 time
.....

  Out &H288, &HFF ' disconnect
form_9 = 0
Do While form_9 <= 8 ' 9 loop
'%%%%%%%% set delay time before connect 30 Sec
  i9 = 0
  Do While i9 <= 4 ' 6 sec x 5 loop = 30 Sec
    For x = 1 To 5000000
      A = 1
    Next x
    i9 = i9 + 1
  Loop
  '%%%%%%%%%%
  Out &H288, &H0 'connect
'$$$$$$$$ Connect 3 Minute $$$$$$$$$$
  con9 = 0

```

```

Do While con9 <= 30 ' 6 sec x 31 loop = 3 Min ***
  For x = 1 To 5000000
    A = 1
  Next x
  con9 = con9 + 1
  Loop
  '$$$$$$$$$ End connect 3 minute $$$$$$$$$
  Out &H288, &HFF 'disconnect
  form_9 = form_9 + 1
Loop 'loop form_9
  '%%%%% set delay time after disconnect 27 Min
  i9 = 0
  Do While i9 <= 269 ' 6 Sec x 270 loop = 1620 Sec( 27 Min)
    For x = 1 To 5000000
      A = 1
    Next x
    i9 = i9 + 1
  Loop
  '%%%%%%%%%%
  ' So that this routine is time leftover 1.5 Min
  '          (0.5 x 9)+(3 x 9)+ 27 = 58.5 Min
  .....,.....

End Function
Function form_10() As String
Dim form_10 As Long
Dim i10 As Long
Dim con10 As Long
Dim x As Long
Out &H283, &H80 ' set card is outport
Out &H287, &H80 ' set card is outport
Out &H28B, &H80 ' set card is outport
'10 time
.....

  Out &H288, &HFF ' disconnect
form_10 = 0
Do While form_10 <= 9 ' 10 loop
  '%%%%% set delay time before connect 30 Sec
  i10 = 0
  Do While i10 <= 4 ' 6 sec x 5 loop = 30 Sec

```

```

For x = 1 To 5000000
    A = 1
Next x
i10 = i10 + 1
Loop
'%%%%%%%%%%
Out &H288, &H0 'connect
$$$$$$$$ Connect 3 Minute $$$$$$$$
con10 = 0
Do While con10 <= 30 ' 6 sec x 31 loop = 3 Min ***
    For x = 1 To 5000000
        A = 1
    Next x
    con10 = con10 + 1
    Loop
$$$$$$$$ End connect 3 minute $$$$$$$$
    Out &H288, &HFF 'disconnect
    form_10 = form_10 + 1
Loop 'loop form_10
'%%%%%%%% set delay time after disconnect 23 Min
i10 = 0
Do While i10 <= 229 ' 6 Sec x 230 loop = 1380 Sec( 23 Min)
    For x = 1 To 5000000
        A = 1
    Next x
    i10 = i10 + 1
    Loop
'%%%%%%%%%%
' So that this routine is time leftover 0.5 Min
'          (0.5 x 10)+(3 x 10)+ 23 = 58 Min
.....

End Function
Function form_11() As String
Dim form_11 As Long
Dim i11 As Long
Dim con11 As Long
Dim x As Long
Out &H283, &H80 ' set card is outport
Out &H287, &H80 ' set card is outport

```

Out &H28B, &H80 ' set card is output

'11 time

```

.....

    Out &H288, &HFF ' disconnect
form_11 = 0
Do While form_11 <= 10 ' 11 loop
'%%%%%%%% set delay time before connect 30 Sec
    i11 = 0
    Do While i11 <= 4 ' 6 sec x 5 loop = 30 Sec
        For x = 1 To 5000000
            A = 1
        Next x
        i11 = i11 + 1
    Loop
'%%%%%%%%%%
    Out &H288, &H0 'connect
'$$$$$$$$ Connect 3 Minute SSSSSSSSSSS$
    con11 = 0
    Do While con11 <= 30 ' 6 sec x 31 loop = 3 Min ***
        For x = 1 To 5000000
            A = 1
        Next x
        con11 = con11 + 1
    Loop
'$$$$$$$$ End connect 3 minute SSSSSSSSS$
    Out &H288, &HFF 'disconnect
    form_11 = form_11 + 1
Loop 'loop form_11
'%%%%%%%% set delay time after disconnect 19 Min
    i11 = 0
    Do While i11 <= 189 ' 6 Sec x 190 loop = 1140 Sec( 19 Min)
        For x = 1 To 5000000
            A = 1
        Next x
        i11 = i11 + 1
    Loop
'%%%%%%%%%%
' So that this routine is time leftover 0.5 Min
'          (0.5 x 11)+(3 x 11)+ 19 = 57.5 Min

```

```

.....
End Function
Function form_12() As String
Dim form_12 As Long
Dim i12 As Long
Dim con12 As Long
Dim x As Long
Out &H283, &H80 ' set card is output
Out &H287, &H80 ' set card is output
Out &H28B, &H80 ' set card is output
'12 time
.....

    Out &H288, &HFF ' disconnect
form_12 = 0
Do While form_12 <= 11 ' 12 loop
'%%%%%%%% set delay time before connect 30 Sec
    i12 = 0
    Do While i12 <= 4 ' 6 sec x 5 loop = 30 Sec
        For x = 1 To 5000000
            A = 1
        Next x
        i12 = i12 + 1
    Loop
    '%%%%%%%%%%
    Out &H288, &H0 'connect
'SSSSSSSSSSS Connect 3 Minute SSSSSSSSSSS
    con12 = 0
    Do While con12 <= 30 ' 6 sec x 31 loop = 3 Min ***
        For x = 1 To 5000000
            A = 1
        Next x
        con12 = con12 + 1
    Loop
'SSSSSSSSSSS End connect 3 minute SSSSSSSSS
    Out &H288, &HFF 'disconnect
    form_12 = form_12 + 1
Loop 'loop form_12

```

```

'%%%%%%%% set delay time after disconnect 15 Min
i12 = 0
Do While i12 <= 149 ' 6 Sec x 150 loop = 900 Sec( 15 Min)
  For x = 1 To 5000000
    A = 1
  Next x
  i12 = i12 + 1
Loop
'%%%%%%%%%%
' So that this routine is time leftover 0.5 Min
'      (0.5 x 12)+(3 x 12)+ 15 = 57 Min
'.....

End Function
Function form_13() As String
Dim form_13 As Long
Dim i13 As Long
Dim con13 As Long
Dim x As Long
Out &H283, &H80 ' set card is outport
Out &H287, &H80 ' set card is outport
Out &H28B, &H80 ' set card is outport
'13 time
'.....

  Out &H288, &HFF ' disconnect
form_13 = 0
Do While form_13 <= 12 ' 13 loop
'%%%%%%%% set delay time before connect 30 Sec
  i13 = 0
  Do While i13 <= 4 ' 6 sec x 5 loop = 30 Sec
    For x = 1 To 5000000
      A = 1
    Next x
    i13 = i13 + 1
  Loop
  '%%%%%%%%%%
  Out &H288, &H0 'connect
'$$$$$$$$ Connect 3 Minute $$$$$$$$$$$$
  con13 = 0
  Do While con13 <= 30 ' 6 sec x 31 loop = 3 Min ***

```

```

For x = 1 To 5000000
    A = 1
Next x
con13 = con13 + 1
Loop
'$$$$$$$$ End connect 3 minute $$$$$$$$
Out &H288, &HFF 'disconnect
form_13 = form_13 + 1
Loop 'loop form_13
'%%%% set delay time after disconnect 7 Min
i13 = 0
Do While i13 <= 119 ' 6 Sec x 120 loop = 720 Sec( 12 Min)
    For x = 1 To 5000000
        A = 1
    Next x
    i13 = i13 + 1
    Loop
    '%%%%%%%%%%%%
' So that this routine is time leftover 2.5 Min
'          (0.5 x 13)+(3 x 13)+ 12 = 57.5 Min
.....

End Function
Function form_14() As String
Dim form_14 As Long
Dim i14 As Long
Dim con14 As Long
Dim x As Long
Out &H283, &H80 ' set card is output
Out &H287, &H80 ' set card is output
Out &H28B, &H80 ' set card is output
'14 time
.....

    Out &H288, &HFF ' disconnect
form_14 = 0
Do While form_14 <= 13 ' 14 loop
'%%%% set delay time before connect 30 Sec
i14 = 0
Do While i14 <= 4 ' 6 sec x 5 loop = 30 Sec
    For x = 1 To 5000000

```

```

    A = 1
  Next x
i14 = i14 + 1
Loop
'%%%%%%%%%%
Out &H288, &H0 'connect
$$$$$$$$ Connect 3 Minute $$$$$$$$
con14 = 0
Do While con14 <= 30 ' 6 sec x 31 loop = 3 Min ***
  For x = 1 To 5000000
    A = 1
  Next x
  con14 = con14 + 1
Loop
'$$$$$$$$ End connect 3 minute $$$$$$$$
Out &H288, &HFF 'disconnect
form_14 = form_14 + 1
Loop 'loop form_14
'%%%%%%%% set delay time after disconnect 9 Min
i14 = 0
Do While i14 <= 88 ' 6 Sec x 89 loop = 534 Sec( 8.9 Min)
  For x = 1 To 5000000
    A = 1
  Next x
  i14 = i14 + 1
Loop
'%%%%%%%%%%
' So that this routine is time leftover ~ 2 Min
'          (0.5 x 14)+(3 x 14)+ 9 = ~ 58 Min
.....

End Function
Function form_15() As String
Dim form_15 As Long
Dim i15 As Long
Dim con15 As Long
Dim x As Long
Out &H283, &H80 ' set card is output
Out &H287, &H80 ' set card is output
Out &H28B, &H80 ' set card is output

```

```

'15 time
*****
      Out &H288, &HFF ' disconnect
form_15 = 0
Do While form_15 <= 14 ' 15 loop , usage 15 times
'%%%%%%%% set delay time before connect 30 Sec
      i15 = 0
      Do While i15 <= 4 ' 6 sec x 5 loop = 30 Sec
        For x = 1 To 5000000
          A = 1
        Next x
        i15 = i15 + 1
      Loop
      '%%%%%%%%%%
      Out &H288, &H0 'connect
'$$$$$$$$ Connect 3 Minute $$$$$$$$$$
      con15 = 0
      Do While con15 <= 30 ' 6 sec x 31 loop = 3 Min ***
        For x = 1 To 5000000
          A = 1
        Next x
        con15 = con15 + 1
      Loop
'$$$$$$$$ End connect 3 minute $$$$$$$$$$
      Out &H288, &HFF 'disconnect
      form_15 = form_15 + 1
Loop 'loop form_15
'%%%%%%%% set delay time after disconnect 7 Min
      i15 = 0
      Do While i15 <= 69 ' 6 Sec x 70 loop = 420 Sec( 7 Min)
        For x = 1 To 5000000
          A = 1
        Next x
        i15 = i15 + 1
      Loop
      '%%%%%%%%%%
' So that this routine is time leftover 0.5 Min
'      (0.5 x 15)+(3 x 15)+ 7 = 59.5 Min

```

```

*****
End Function
Private Sub Command1_Click()
Dim L55(1 To 120) As Integer
Dim tt As Integer
Dim h As Integer
Dim mt As Integer
Dim x As Integer
x = 1 ' set index start of table load
'%%%%%%%%%%
' Table load type day 50% night 50%
L55(1) = 4 '
L55(2) = 4
.
. ( ข้อมูลไหลต่อเนื่องแบบ)
.
L55(110) = 5
L55(120) = 5
'%%%%%%%%%% End Table load%%%%%%%%%%
'%%%%%%%%%% SET DEFAULT VALUE %%%%%%%%%%%
day_ini = 1
day_end = 5 ' set end of day
'%%%%%%%%%%
'%%%%%%%%%% START PROGRAM %%%%%%%%%%%
' Set Out port @ I/O Card 8255 #2
Out &H283, &H80 'out port
Out &H287, &H80 'out port
Out &H28B, &H80 'out port
Do While day_ini <= day_end
    h = Hour(Time)
    mt = Minute(Time)
    tt = h + (mt / 100)
    loop_24 = 0
    Do While loop_24 <= 23 '*** START LOOP 24 HOURS ***
        If (tt >= h And tt <= (h + 0.02)) Then
' Condition If , it's to start at beginning of hour,and neglect any time
' so that if program start user is get approximate time by self

```

```
If L55(x) = 1 Then
    form_1
Elseif L55(x) = 2 Then
    form_2
Elseif L55(x) = 3 Then
    form_3
Elseif L55(x) = 4 Then
    form_4
Elseif L55(x) = 5 Then
    form_5
Else: L55(x) = 6
    form_6
End If
x = x + 1 ' set index next hour for load
loop_24 = loop_24 + 1 ' set index next hour for counter
Else
    h = Hour(Time)
    mt = Minute(Time)
    tt = h + (mt / 100)
End If
Loop 'END LOOP 24 HOURS
day_ini = day_ini + 1
Loop
    Print "Finish program"
End Sub
Private Sub Command2_Click()
End
End Sub
```

ภาคผนวก ง.

ข้อมูลเทคนิคอุปกรณ์ที่ใช้ในการทดลอง

มหาวิทยาลัยเชียงใหม่
Chiang Mai University


CARD ET-PC 8255

การทำงานของ ET-PC 8255

Card ET-PC 8255 ประกอบไปด้วย 2 ส่วนใหญ่ ๆ คือ ส่วน IC 8255 ซึ่งเป็น IC ทำหน้าที่เป็น อินพุทพอร์ต หรือ เอาท์พุทพอร์ต และส่วนของวงจร IC DECODE (เลือกตำแหน่งของ PORT 8255) คือ IC 74LS688 , 74LS139 และ DIP SW.


การใช้งาน IC 8255

IC 8255 นี้จะเป็น IC ซึ่งประกอบด้วยพอร์ตใช้งาน 3 พอร์ต และอีก 1 พอร์ต ควบคุม ก่อนที่เราใช้งาน 8255 เราจะต้องส่งข้อมูลไปให้ยังพอร์ตควบคุมก่อนว่าจะให้พอร์ตทั้ง 3 พอร์ต ของ 8255 ที่เหลือนั้นทำหน้าที่อะไรเป็น อินพุทพอร์ต หรือ เอาท์พุทพอร์ต เราจะต้องเป็นผู้กำหนด Control Code port ควบคุมดังรูป




สถาปัตยกรรมของ IC 8255

Pin Configuration



Block Diagram



PIN NAMES	
D0-D7	DATA BUS (BI-DIRECTIONAL)
RESET	RESET INPUT
CS	CHIP SELECT
RD	READ INPUT
WR	WRITE INPUT
AD A1	PORT ADDRESS
PA7-PA0	PORT A (BIT)
PB7-PB0	PORT B (BIT)
PC7-PC0	PORT C (BIT)
VCC	+5 VOLTS
GND	0 VOLTS



ข้อมูลควบคุมพอร์ตต่าง ๆ

ET-PC8255 ETT CO., LTD.



ETT

Mode 0 Configurations



CONTROL WORD #0





CONTROL WORD #4





CONTROL WORD #1





CONTROL WORD #5





CONTROL WORD #2





CONTROL WORD #6





CONTROL WORD #3





CONTROL WORD #7





CONTROL WORD #8





CONTROL WORD #12





CONTROL WORD #9





CONTROL WORD #13





CONTROL WORD #10





CONTROL WORD #14



CONTROL WORD #11



CONTROL WORD #15




CARD ET- AD

การทำงานของ CARD ET-AD

ET-AD เป็นการ์ดประเภทเปลี่ยนแปลงสัญญาณจากแอนะล็อกเป็นดิจิทัล (Analog to Digital) ซึ่งใช้ IC 7107 เป็น A to D ขนาด $3 \frac{1}{2}$ Digit หรือ 0 – 1999 ระดับ หรือเทียบได้ขนาด 10 บิต สามารถที่จะประยุกต์วัดค่าต่าง ๆ ได้ เช่น


- เครื่องวัดความต้านทาน
- เครื่องวัดอุณหภูมิ
- เครื่องวัดแรงดัน

รูป CARD ET-AD



ต่อกับ I/O PORT ของ CP32BASIC
หรือ 7210 Z80

ต่อกับ 8255 PORT ของ
ET-BOARD V 3.0



Specifications ICL7106, ICL7107

Absolute Maximum Ratings

Supply Voltage	
ICL7106, V+ to V-	15V
ICL7107, V+ to GND	6V
ICL7107, V- to GND	-9V
Analog Input Voltage (Either Input) (Note 1)	V+ to V-
Reference Input Voltage (Either Input)	V+ to V-
Clock Input	
ICL7106	TEST to V+
ICL7107	GND to V+

Thermal Information

Thermal Resistance (MAX, See Note 1)	θ_{JA}
40 Pin Plastic Package	50°C/W
44 Pin MQFP Package	80°C/W
Maximum Power Dissipation	
ICL7106	1.0W
ICL7107	1.2W
Operating Temperature Range	0°C to +70°C
Storage Temperature Range	-65°C to +150°C
Lead Temperature (Soldering 10s Max)	+265°C
Junction Temperature	+150°C

CAUTION: Stresses above those listed in "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress only rating and operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied.

Electrical Specifications (Note 3)

PARAMETERS	TEST CONDITIONS	MIN	TYP	MAX	UNIT
SYSTEM PERFORMANCE					
Zero Input Reading	$V_{IN} = 0.0V$, Full-Scale = 200mV	-000.0	±000.0	+000.0	Digital Reading
Ratiometric Reading	$V_{IN} = V_{REF}$, $V_{REF} = 100mV$	999	999/ 1000	1000	Digital Reading
Rollover Error	$-V_{IN} = +V_{IN} \approx 200mV$ Difference in Reading for Equal Positive and Negative Inputs Near Full-Scale	-	±0.2	±1	Counts
Linearity	Full-Scale = 200mV or Full-Scale = 2V Maximum Deviation from Best Straight Line Fit (Note 5)	-	±0.2	±1	Counts
Common Mode Rejection Ratio	$V_{CM} = 1V$, $V_{IN} = 0V$, Full-Scale = 200mV (Note 5)	-	50	-	μV/V
Noise	$V_{IN} = 0V$, Full-Scale = 200mV (Pk-Pk Value Not Exceeded 95% of Time)	-	15	-	μV
Leakage Current Input	$V_{IN} = 0$ (Note 5)	-	1	10	μA
Zero Reading Drift	$V_{IN} = 0$, $0^\circ < T_A < +70^\circ C$ (Note 5)	-	0.2	1	μV/°C
Scale Factor Temperature Coefficient	$V_{IN} = 199mV$, $0^\circ < T_A < +70^\circ C$, (Ext. Ref. 0ppm/°C) (Note 5)	-	1	5	ppm/°C
End Power Supply Character V- Supply Current	$V_{IN} = 0$ (Does Not Include LED Current for ICL7107)	-	0.8	1.8	mA
End Power Supply Character V- Supply Current	ICL7107 Only	-	0.6	1.8	mA
COMMON Pin Analog Common Voltage	25kΩ Between Common and Positive Supply (With Respect to - Supply)	2.4	2.8	3.2	V
Temperature Coefficient of Analog Common	25kΩ Between Common and Positive Supply (With Respect to + Supply)	-	80	-	ppm/°C
DISPLAY DRIVER ICL7106 ONLY					
Pk-Pk Segment Drive Voltage	V+ to V- = 9V, (Note 4)	4	5	6	V
Pk-Pk Backplane Drive Voltage					

ICL7106, ICL7107

Electrical Specifications (Note 3) (Continued)

PARAMETERS	TEST CONDITIONS	MIN	TYP	MAX	UNIT
ICL7107 ONLY					
Segment Sinking Current (Except Pin 19 and 20)	$V_{+} = 5V$, Segment Voltage = 3V	5	8	-	mA
Pin 19 Only		10	16	-	mA
Pin 20 Only		4	7	-	mA

NOTES.

1. Input voltages may exceed the supply voltages provided the input current is limited to $\pm 100\mu A$.
2. Dissipation rating assumes device is mounted with all leads soldered to printed circuit board.
3. Unless otherwise noted, specifications apply to both the ICL7106 and ICL7107 at $T_A = +25^{\circ}C$. $f_{CLOCK} = 48kHz$. ICL7106 is tested in the circuit of Figure 1. ICL7107 is tested in the circuit of Figure 2.
4. Back plane drive is in phase with segment drive for 'off' segment, 180° out of phase for 'on' segment. Frequency is 20 times conversion rate. Average DC component is less than 50mV.
5. Not tested, guaranteed by design.

Typical Applications and Test Circuits




FIGURE 1: ICL7106 TEST CIRCUIT AND TYPICAL APPLICATION WITH LCD DISPLAY COMPONENTS SELECTED FOR 200mV FULL-SCALE





FIGURE 2: ICL7107 TEST CIRCUIT AND TYPICAL APPLICATION WITH LED DISPLAY COMPONENTS SELECTED FOR 200mV FULL-SCALE

Closed Loop Current Sensors

A closed loop current sensor consists of a Hall sensor mounted in an air gap of a magnetic core, a coil wound around the core and a current amplifier. The current carrying conductor placed through the aperture of the sensor produces a magnetic field that is proportionate to the current. This field is concentrated by the core and sensed by the Hall sensor. The Hall sensor is connected to the input of the current amplifier, which drives the coil. The current through the coil produces



an opposing field to that provided by the current through the aperture, thus the flux in the core is constantly driven to zero. The coil connects to the output of the sensor. Therefore the output is a current proportional to the aperture current, multiplied by the number of turns on the coil. A sensor with a 1000 turn coil provides an output of 1mA per ampere. The current output is converted to a voltage by connecting a resistor between the output of the sensor and ground. The

output is scaled by selecting the resistor value. Closed loop sensors measure DC and AC currents and provide electrical isolation. They offer fast response, high linearity and low temperature drift. The current output of the closed loop sensor is relatively immune to electrical noise. They are the sensor of choice when high accuracy is essential.

- Fast Response
- Excellent linearity
- Wide bandwidth
- Low temperature drift


Model	Nominal Current (A)	Linearity (%)	Frequency	Output (mA at 1V)	Aperture Section (mm)	Page(s)
CLN-25	25	0.2	dc to 150 kHz	25	0.83 x 0.39	28-31
CLN-50	50	0.1	dc to 150 kHz	50	0.83 x 0.39	32-35
CLN-50SP1	50	0.1	dc to 150 kHz	50	PCB Connection	36-37
CLN-100	100	0.1	dc to 150 kHz	100	0.63 x 0.38	34-35
CLN-100SP1	100	0.2	dc to 150 kHz	100	PCB Connection	36-37
CLN-200	200	0.1	dc to 150 kHz	200	0.53 x 0.39	38-39
CLN-300	300	0.1	dc to 150 kHz	300	0.9	38-39
CLN-300SP1	300	0.1	dc to 150 kHz	300	Breadboard	40-41
CLN-500	500	0.1	dc to 150 kHz	500	1.02	42-43
CLN-500SP1	500	0.1	dc to 150 kHz	500	Breadboard	40-41
CLN-1000	1000	0.1	dc to 150 kHz	1000	1.02	42-43
CLO-500	500	0.1	dc to 100 kHz	500	1.025	44-45

Note: Due to continuous process improvement, all specifications listed in this catalog subject to change without notice.

Model CLN-25

Mechanical Dimensions

All dimensions are in inches (millimeters)



Measuring Range Table

Number of Turns at I_m	I_m (A)	Peak (A)	Normal output Current (mA)	Turn Ratio	Insertion Loss Resistance (mΩ)	Insertion Loss Inductance (μH)	Recommended Connections
1	25	38	25	1/1000	0.3	0.023	IN 64321 OUT 67880
2	12	18	24	2/1000	1.1	0.09	IN 64321 OUT 47880
3	8	12	24	3/1000	2.5	0.21	IN 64321 OUT 67880
4	6	8	24	4/1000	4.4	0.37	IN 64321 OUT 67880
5	5	7	25	5/1000	6.3	0.58	IN 64321 OUT 67880

Note: Due to continuous process improvement, all specifications listed in this catalog subject to change without notice.

Model CLN-25

Description

The Model CLN-25 is a closed loop Hall effect current sensor that accurately measures dc and ac currents and provides electrical isolation between the current carrying conductor and the output of the sensor.

Electrical Specifications

Nominal current (I_N)	25 Ampere turns rms	
Measuring range	0 to 36 Ampere turns (A.t.)	
Sense resistor	<u>R. min.</u>	<u>R. max.</u>
with ± 12 V at 25 A.t. peak	100 ohms	200 ohms
at 36 A.t. peak	100 ohms	140 ohms
with ± 15 V at 25 A.t. peak	100 ohms	320 ohms
at 36 A.t. peak	100 ohms	190 ohms
Nominal analog output current	25 mA	
Turns ratio	1-2-3-4-5:1000	
Overall accuracy at 25 °C and ± 12 V	$\pm 0.7\%$ of I_N	
Overall accuracy at 25 °C and ± 15 V	$\pm 0.5\%$ of I_N	
Supply voltage (Vdc)	± 12 to ± 15 ($\pm 5\%$)	
Dielectric strength	between the current carrying conductor and the output of the sensor: 5 kV rms/50 Hz/1 min.	

Accuracy-Dynamic Performance

	<u>Typical</u>	<u>Max.</u>
Zero current offset at 25 °C (± 15 V)	± 0.05 mA	± 0.15 mA
Residual current offset after		
an overload of $3 \times I_N$	± 0.05 mA	± 0.15 mA
Offset current temperature drift (± 15 V)		
(between 0 °C and +25 °C)	± 0.06 mA	± 0.25 mA
(between -25 °C and +70 °C)	± 0.1 mA	± 0.35 mA
Linearity	better than $\pm 0.2\%$	
Response time	less than 1 μ s	
di/dt accurately followed	better than 50 A/ μ s	
Bandwidth	0 to 150 kHz (-1 dB)	

General Information

Operating temperature	-40 °C to +85 °C
Storage temperature	-40 °C to +90 °C
Current drain	10 mA (at ± 15 V) plus output current
Coil resistance	110 ohms (at 70 °C)
Package	Flame retarded plastic case
Weight	16 grams
Mounting	Designed to mount directly on PCB via through hole connection pins
Output reference	To obtain a positive output on the terminal, marked "O/P", current must flow from terminals 1,2,3,4 and 5 to terminals 10,9,8,7 and 6 (conventional flow)

Notes

1. The CLN-25 offers a choice of 5 measuring ranges (see table)
2. Due to continuous process improvement, all specifications listed in this catalog subject to change without notice.

ประวัติผู้เขียน

ชื่อ นายศุภกิจ แสงทอง
วัน เดือน ปี เกิด 19 ตุลาคม 2510
ประวัติการศึกษา สำเร็จการศึกษาระดับปริญญาตรี ครุศาสตร์อุตสาหกรรม
(สาขาวิศวกรรมไฟฟ้า) จากสถาบันเทคโนโลยีราชมงคล
จังหวัดเชียงใหม่ เมื่อปีการศึกษา 2535
ประสบการณ์ในการทำงาน สายนงานวิศวกร แผนกอาคารและการกำลัง
เขตโทรศัพท์ภาคเหนือที่ 1
องค์การโทรศัพท์แห่งประเทศไทย
ตั้งแต่ ปี พ.ศ. 2535 - ปัจจุบัน